



STUDYDADDY

**Get Homework Help
From Expert Tutor**

Get Help

Power Systems Theory & Design
Theoretical Otto Cycle
Part I → Reversible Adiabatic Compression

HW #8a

Given: $\gamma/\gamma_{ec} = 0.70, 1.0, 1.40$ (3 cases)

Same as class example { Fuel: Octane
Compression Ratio, $r_c = 9.0$
 $T_1 = 300\text{ K}$, $P_1 = 100\text{ kPa}$, $V_1 = 0.5\text{ Liters}$

Determine: T_2 (degrees K)
 P_2 (kPa)
 $\overline{W}_{1-2} = W_{\text{compression}}$ (KJ/compression stroke)

Determine for all three cases, γ/γ_{ec} , given above.
(Note: $\gamma/\gamma_{ec} = 1.0$ is exactly the class example)

Power Systems Theory & Design HW# 86
Theoretical Otto Cycle
Part II \rightarrow Constant Volume, Ideal Complete
Adiabatic Combustion.

Given: $\gamma/\gamma_{cc} = 0.70, 1.0, 1.40$ (3 cases)
Fuel: Octane
Use T_2, P_2 and mole numbers & mole fractions of reactants
from part I.

Determine: T_3 (degrees K)
 P_3 (KPa)
mole fractions products ($y_{CO}, y_{CO_2}, y_{H_2O}, y_{O_2}, y_{N_2}$)
mole numbers of products ($n_{CO}, n_{CO_2}, n_{H_2O}, n_{O_2}, n_{N_2},$
 n_{tot} (products))

Determine for all three cases, γ/γ_{cc} , given above.
(Note: $\gamma/\gamma_{cc} = 1.0$ is exactly the class example,
where $T_2 = 623.367K, P_2 = 1870.10 kPa$, etc.)

Power Systems Theory & Design
Part III Reversible Adiabatic Expansion

HW# 8c

Given: $Y_{f/c} = 0.70, 1.0, 1.40$ (3 cases)

Use T_3, P_3 , and mole fractions and mole numbers of the products of combustion from Part II.

Determine: T_4 (degrees K)
 P_4 (kPa)
 ${}_3W_4 = W_{\text{Expansion}}$ (KJ/expansion stroke)

Determine for all three cases, $Y_{f/c}$, given above.

(Note: $Y_{f/c} = 1.0$ is exactly the class example, where $T_3 = 3142.23 \text{ K}$, $P_3 = 9972.04 \text{ kPa}$,

$y_{\text{CO}} = 0$, $y_{\text{CO}_2} = 0.125$, $y_{\text{H}_2\text{O}} = 0.140625$, $y_{\text{O}_2} = 0$, $y_{\text{N}_2} = 0.734375$,
 $n_{\text{CO}} = 0$, $n_{\text{CO}_2} = 2.65062 \text{ E-}06 \text{ kmoles}$, $n_{\text{H}_2\text{O}} = 2.98194 \text{ E-}06 \text{ kmoles}$,
 $n_{\text{O}_2} = 0$, $n_{\text{N}_2} = 1.55724 \text{ E-}05 \text{ kmoles}$, $n_{\text{tot (products)}}$)



STUDYDADDY

**Get Homework Help
From Expert Tutor**

Get Help